# **TOOLS & TEST EQUIPMENT**

## HANDHELD PORTABLE ANALOG SIGNAL GENERATOR

**MODEL ASG** 

#### **DESCRIPTION**

[199.9]

The Model ASG is a handheld, battery- or plug-in-power-supply-powered, pocket-size analog signal generator. It generates a 0-10 VDC signal in increments of 1V or a 0-20 mA signal in increments of 2 mA. The LED bar graph visually indicates analog signal level. The Model ASG can also continuously ramp to userdefined minimum or maximum values with user-defined ramptime settings.

#### **FEATURES**

- · Powered by 9V battery or plug-in power supply
- Pocket-sized
- Bar graph LED for signal display
- 0-20 mA (2 mA increments)
- 0-10 VDC (1 VDC increments)
- Ramp function to minimum and maximum values
- Variable ramp function timing
- Low-battery indication
- User-defined auto shutoff times for battery conservation
- Separate milliamp and voltage output jacks
- 6' (1.83m) leads with alligator clips
- Up to 30 hours continuous use on a single battery
- Perfect for loop-powered circuits and externally-powered circuits





## **SPECIFICATIONS**

**Power** 9V battery or 120 VAC plug-in

power supply

Output 0-20 mA (2 mA increments)

0-10 VDC (1 VDC increments)

Load impedance

Voltage 1000Ω minimum Current  $300\Omega$  maximum

Resolution

Current 2 mA 1 VDC Voltage

Accuracy (@ 72°F)

±0.5% FS or ±0.1 mA Current ±0.5% FS or ±0.05 VDC Voltage Operating temp 32° to 122°F (0° to 50°C) 4.7"H x 2.40"W x 0.85"D **Dimensions** (11.9 x 6.1 x 2.2 cm)

Weight Ramping time intervals Auto shutoff times **Accessories included** 


14 oz (0.4 kg) with accessories 2-20 second (2-second increments) 2-20 minute. (2-minute. increments) 9V battery, 120 VAC plug-in power supply, 6' (1.83m) wire leads,

carrying case

RoHS Agency Warranty 18 months

## **APPLICATIONS**

- Troubleshooting transmitters, transducers, and actuators
- Calibrating transducers, digital displays, and other analog signal devices



## **ORDERING INFORMATION**

MODEL DESCRIPTION

**ASG** mA/VDC handheld portable analog signal generator with accessories