

# Security Expert Security Purpose Mini Output Expansion



The Security Expert Security Purpose Mini Output Expansion provides the control of 8 high current Form C relay outputs to the Security Expert system, an advanced technology security product providing seamless and powerful integration of access, security and building automation. The Output Expansion provides extensive hardware advancements that allow flexible and structured control of lighting and HVAC systems and is designed for use with industry standard DIN Rail mounting.

## Feature Highlights

- 8 Form C relays capable of switching resistive loads up to 5 Amps
- Compact two-tier half DIN rail module design
- High performance 32 Bit processor
- Secure encrypted RS-485 module communications
- Online and remote upgradable firmware
- LED indicators to show state of all onboard relays
- Ideal for connection in an electrical switch room to control signage, lighting and building automation

## Power Supply

Device power is supplied from a 12VDC input. Ultra low current requirements ensure cost effective power distribution.

## Smaller Footprint

The compact module design takes up less valuable real estate to provide more control in less space

## Communication

Single RS-485 communication interface port used for all network communication functions and interconnection to other modules.

## Upgradable Firmware

Utilizing the latest flash technology and high performance communication mediums, the firmware can be updated using the Loadit utility over the system module network.

## Connectivity and System Expansion

Expanding the Security Expert System with outputs from the Security Expert Security Purpose Mini Output Expansion allows convenient, cost effective expansion and added benefit of:

- 8 multi-function outputs for use in any programmable output entry
- Ideal for connection in an electrical switch room to control signage, lighting and building automation
- Address configuration of the Output Expansion interface is achieved using the address programming feature of the Security Expert System Controller
- Outputs can be configured to automatically turn on when powered up, during communication failure, or resume to their previous state

## Technical Specifications

Power Supply	
DC Input Voltage	11-14VDC
DC Output Voltage (DC IN Pass-Through)	10.83-14.0VDC 0.7A (Typical) Electronic Shutdown at 1.1A
Operating Current	80mA (Typical)
Total Combined Current*	3.25A (Max)
Low Voltage Cutout	8.7VDC
Low Voltage Restore	10.5VDC
Communication	
RS-485	Module Network
Outputs	
PGM Outputs	8 Form C relays - 5A N.O/N.C. at 30 VAC/DC resistive/inductive
Dimensions	
Dimensions (L x W x H)	78 x 90 x 60mm (3.07 x 3.54 x 2.36")
Weight	231g (15oz)
Temperature	
Operating	0°-50°C (32° - 122°F)
Storage	-10° - 85°C (14° - 185°F)
Humidity	0%-93% non-condensing, indoor use only (relative humidity)

\* The Total Combined Current refers to the current that will be drawn from the external power supply to supply the Output Expansion and any devices connected to its outputs. The Auxiliary outputs are directly connected via electronic fuses to the N+ N- input terminals, and the maximum current is governed by the trip level of these fuses.

It is important that the unit is installed in a dry cool location that is not affected by humidity. Do not locate the unit in air conditioning or a boiler room that can exceed the temperature or humidity specifications.

## Ordering Information

SP-MO8	Security Expert Security Purpose Mini Output Expansion
--------	--

## Regulatory Notices

### Federal Communications Commission (FCC)

FCC Rules and Regulations CFR 47, Part 15, Class A.

This equipment complies with the limits for a Class A digital device, pursuant to Part 15 of the FCC rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference; (2) This device must accept any interference received, including interference that may cause undesired operation.

### Industry Canada

ICES-003

This is a Class A digital device that meets all requirements of the Canadian Interference-Causing Equipment Regulations.

CAN ICES-3 (A)/NMB-3(A)

### RCM (Australian Communications and Media Authority (ACMA))

This equipment carries the RCM label and complies with EMC and radio communications regulations of the Australian Communications and Media Authority (ACMA) governing the Australian and New Zealand (AS/NZS) communities.

### CE – Compliance with European Union (EU)

Conforms to European Union (EU) Low Voltage Directive (LVD) 2014/35/EU, Electro-Magnetic Compatibility (EMC) Directive 2014/30/EU and RoHS Recast (RoHS2) Directive: 2011/65/EU.

This equipment complies with the rules of the Official Journal of the European Union for governing the Self Declaration of the CE Marking for the European Union as specified in the above directive(s).