# Product data sheet Characteristics

# BMXAMO0802 analog output module M340 - 8 outputs





### Main

		o
Range of product	Modicon M340 automation platform	eci <u>f</u>
Product or component type	Analog output module	
Electrical connection	1 connector 20 ways	
Input output isolation	Non isolated	o D O

#### Complementary

Complementary		
Measurement error	<= 0.25 % of full scale 060 °C 0.1 % of full scale 25 °C	
Temperature drift	45 ppm/°C 020 mA 45 ppm/°C 420 mA	
Common mode between channels	>= 80 dB	
Isolation voltage	1400 V DC between channels and ground 1400 V DC between channels and bus	
Detection type	Open circuit 420 mA Short circuit 020 mA	
Load impedance ohmic	<= 350 Ohm 020 mA <= 350 Ohm 420 mA	
Output level	High level	
Analogue output number	8	
Analogue output type	Current 020 mA Current 420 mA	
Analogue output resolution	15 bits + sign	
Supply	Internal power supply via rack	
Conversion time	<= 4 ms	
Maximum conversion value	021 mA 020 mA 021 mA 420 mA	
Fallback mode	Configurable Predefined	
Status LED	1 LED green RUN 1 LED per channel green channel diagnostic 1 LED red ERR 1 LED red I/O	

Product weight	0.15 kg
Current consumption	150 mA at 3.3 V DC 74 mA at 24 V DC

## Environment

Ambient air temperature for operation	060 °C
Relative humidity	1095 % without condensation
IP degree of protection	IP20
Protective treatment	TC

## Offer Sustainability

Green Premium product	
Compliant - since 0901 - Schneider Electric declaration of conformity	
Schneider Electric declaration of conformity	
Reference contains SVHC above the threshold - Go to CaP for more details	
Go to CaP for more details	
Available	
Product environmental	
Available	
🚰 End of life manual	
	Compliant - since 0901 - Schneider Electric declaration of conformity  Schneider Electric declaration of conformity  Reference contains SVHC above the threshold - Go to CaP for more details  Go to CaP for more details  Available  Product environmental  Available

## Contractual warranty


Contraction Warranty		
Warranty period	18 months	

## Product data sheet **Dimensions Drawings**

## BMXAMO0802

#### Modules Mounted on Racks

### **Dimensions**




- With removable terminal block (cage, screw or spring). (1)
- With FCN connector.
- (2) (3) On AM1 ED rail: 35 mm wide, 15 mm deep. Only possible with BMXXBP0400/0400H/0600/0600H/0800/0800H rack.

Rack references	a in mm	a in in.
BMXXBP0400 and BMXXBP0400H	242.4	09.54
BMXXBP0600 and BMXXBP0600H	307.6	12.11
BMXXBP0800 and BMXXBP0800H	372.8	14.68
BMXXBP1200 and BMXXBP1200H	503.2	19.81

## Product data sheet Connections and Schema

## BMXAMO0802

## Wiring Diagram



lx + pole input for channel x.

COMx pole input for channel x, COMx are connected together internally.

The current loop is self-powered by the output and does not request any external supply.